CENTRIFUGAL FANS · EC MOTOR

KRUBO EC BACKWARD-CURVED CENTRIFUGAL FANS

CODES SWK-EC190-K230-33 – SWK-EC190-K48-34 | **BRAND: KRUBO** | **12 MODELS**



- 190 MM
- 230 V · 230 V AC
- IP55
- SPEED CONTROL 0~10VDC /PWM
- BALL BEARINGS
- INSULATION B

DESCRIPTION

Krubo EC backward-curved centrifugal fans, listed by Six Winds code and Krubo model. Search either code on sixwinds.com.sa for the full specification of each model.

SIX WINDS CODE	KRUBO MODEL	SIZE	VOLTAGE	POWER	SPEED	AIRFLOW
SWK-EC190-K230-33	K-EC190-K230-33	190 mm	230 V	87 W	3700 rpm	
SWK-EC190-K230-33L	K-EC190-K230-33L	190 mm	230 V	87 W	3300 rpm Frequency: 50/60 Hz	
SWK-EC190-K230-38	K-EC190-K230-38	190 mm			3800 rpm	
SWK-EC190-K230-38J	K-EC190-K230-38J	190 mm	230 V	170 W	4100 rpm	
SWK-EC190-K230-38K	K-EC190-K230-38K	190 mm	230 V	115 W	3800±5%RPM Applications: widely used in cabinet cabinet, air conditioning ,refri	
SWK-EC190-K230-39	K-EC190-K230-39	190 mm	230 V AC	110 W ±10%	3900 rpm/ Min ±3%	
SWK-EC190-K230-41	K-EC190-K230-41	190 mm	230 V	170 W	4100 rpm	
SWK-EC190-K24-34	K-EC190-K24-34	190 mm				
SWK-EC190-K24-38	K-EC190-K24-38	190 mm				
SWK-EC190-K24-40	K-EC190-K24-40	190 mm				
SWK-EC190-K48-26	K-EC190-K48-26	190 mm				
SWK-EC190-K48-34	K-EC190-K48-34	190 mm				

Values as stated by the manufacturer; "/" separates 50 Hz / 60 Hz or speed steps. Other voltages and versions on request.