CENTRIFUGAL FANS · EC MOTOR

KRUBO EC BACKWARD-CURVED CENTRIFUGAL FANS

CODES SWK-EC560-K400-17 – SWK-EC630-R380-14 | **BRAND: KRUBO** | **11 MODELS**



- 560 – 630 MM
- 380 V
- IP54
- SPEED CONTROL 0-10 V DC/PWM
- BALL BEARING
- INSULATION F

DESCRIPTION

Krubo EC backward-curved centrifugal fans, listed by Six Winds code and Krubo model. Search either code on sixwinds.com.sa for the full specification of each model.

SIX WINDS CODE	KRUBO MODEL	SIZE	VOLTAGE	POWER	SPEED	AIRFLOW
SWK-EC560-K400-17	K-EC560-K400-17	560 mm				
SWK-EC560-R380-15	K-EC560-R380-15	560 mm				
SWK-EC560-R380-16	K-EC560-R380-16	560 mm				
SWK-EC560-R380-16Y	K-EC560-R380-16Y	560 mm	380 V	3660 W	1620 rpm	15275 m³/h
SWK-EC560-R380-17Y	K-EC560-R380-17Y	560 mm	380 V	5570 W	1770 rpm	20710 m³/h
SWK-EC630-K380-12	K-EC630-K380-12	630 mm				
SWK-EC630-R380-12	K-EC630-R380-12	630 mm				
SWK-EC630-R380-12Y	K-EC630-R380-12Y	630 mm	380 V	2970 W	1260 rpm	18330 m³/h
SWK-EC630-R380-13	K-EC630-R380-13	630 mm	380 V	4400 W	1800 rpm	
SWK-EC630-R380-13Y	K-EC630-R380-13Y	630 mm				
SWK-EC630-R380-14	K-EC630-R380-14	630 mm	380 V			

Values as stated by the manufacturer; "/" separates 50 Hz / 60 Hz or speed steps. Other voltages and versions on request.